

Efficient readout of flux qubits at degeneracy

A. Käck

*Dept. of Microtechnology and Nanoscience (MC2),
Chalmers University of Technology, 41296 Gothenburg, Sweden*

F.K. Wilhelm*

Department Physik, ASC, and CeNS, Ludwig-Maximilians-University, Theresienstr. 37, 80333 München, Germany

We present a superconducting circuit consisting of a flux qubit and a single-charge transistor serving as a detector. As flux and charge are conjugate, the transistor can detect states of the qubit close to the flux degeneracy point, when the eigenstates are quantum superpositions of fluxes. The coupling has a flip-flop symmetry conserving the total number of excitations, and so the measurement outcome results in the absence or presence of an incoherent tunneling cycle. We evaluate the performance of a practical device and show that it is an attractive tool for measuring at the degeneracy point.

PACS numbers: 03.67.Lx, 74.40.+k, 85.25.Cp

Small Josephson junction circuits are a prototype system for studying generic quantum effects in solid-state physics¹. These devices are a candidate for scalable quantum computing, which requires full and precise control of quantum states in real time. The strong development in this field has led to a number of substantial achievements such as superpositions² and real-time control³ of collective states as well as the control of charge states⁴ and the demonstration of a controlled-not gate⁵. A highly attractive realization of a superconducting qubit is based on magnetic flux states⁶.

A crucial and subtle issue in this effort is the proper understanding and design of the read-out device. Quantum measurements are intrinsically invasive⁷. Ideally, the back-action exclusively consists of instantaneous projection on eigenstates of the measured observable. In general, and specifically for quantum systems such as the Josephson circuits, the back-action consists of two parts: The dephasing process which projects onto the measurement basis, and relaxation which induces transitions between these states leading to errors in the observed variable. The former is inevitable and is an integral part of quantum control protocols, whereas the latter has to be avoided^{1,8}. This aspect makes quantum nondemolition (QND) schemes highly attractive. Thus, for fundamental as well as for practical reasons we are faced with a problem of understanding and ultimately engineering the properties of the read-out device on the quantum level.

Next to the backaction of the detector, any quantum bit realized in a solid-state environment suffers from decoherence induced by the other degrees of freedom of the solid-state environment and of the fluctuations of the control fields — flux noise in the case of flux qubits. Slow fluctuations from the ubiquitous $1/f$ noise in the solid-state environment are particularly destructive, here resulting mostly in critical current fluctuations. Thus, it is very attractive to operate devices at the charge degeneracy point where they are to first order immune to these fluctuations^{3,9,10}. It is possible to achieve a very stable intrinsic bias at that point by flux trapping¹⁰. Fixing

the bias to that point can lead to restrictions on the control parameters. Although operation by AC-pulses is still possible, it is not evident how to read out the state at the end. In a flux-based device operated at flux degeneracy any Hamiltonian-dominated^{1,8} measurement cannot distinguish the energy eigenstates of the system. The natural solution is the measurement of a different variable such as phase⁹, which in the particular case of Ref. [3,9] still requires to move out of the optimum point.

In this letter, we are going to show how, using a Cooper-pair transistor, the state of the qubit can be read out with high fidelity and low unwanted backaction without leaving the degeneracy point. The physical coupling mechanism is based on geometric phases. By appropriate biasing of the transistor and by using a readout channel which filters out unwanted processes, the physical processes are flip-flop transitions between qubit and detector, which lead to a QND-like and quantum limited backaction. We will discuss values of experimentally accessible parameters.

At the degeneracy point, the energy eigenstates are coherent superpositions of flux states, which cannot be discriminated by flux detection. On the other hand, the conjugate variable, the charge, diminishes its intrinsic quantum fluctuations and can in principle be detected.

The circuit we envisage is depicted in Fig. (1). It consists of a three-junction loop frustrated by a magnetic flux close to half a flux quantum, following Ref. [6], one of the islands of which also serves as the island of a single-charge transistor. I.e., it is coupled to voltage sources by small Josephson junctions exhibiting Coulomb blockade, and is subject to an electrostatic gate voltage. For fixing the reference, the different parts of the device are connected to ground either capacitively or galvanically.

In the limit we are interested in, both components are in their generic regimes, i.e. $E_{J,\text{qubit}} \gg E_{c,\text{qubit}} E_{c,\text{SET}} \gg E_{J,\text{SET}}$. Here and henceforth, E_J and $E_c = 2e^2/C$ are the Josephson and charging energies of the respective junction. The interaction between flux and charge is via their mutual geometric phases. Charge moving around mag-




FIG. 1: Proposed circuit for the read out of a flux qubit (three junction loop on the left, junctions 1,2 and 3, controlled by the external flux Φ) at the degeneracy point using an SET (part on the right, other junctions). In order to establish the interaction, the qubit has to have (stray) capacitances to ground, C_4 , C_7 , and C_8 as well.

netic flux acquires an Aharonov-Bohm phase, a flux line moving around a charge acquires an Aharonov-Casher phase^{11,12}. This analogy is a manifestation of vortex-charge duality.

In order to accommodate loop constraints and Kirchhoff rules, we start from a Lagrangian analysis. The Lagrangian of such a coupled circuit can be schematically represented in terms of the junction phases ϕ_i as $\mathcal{L}(\{\phi_i\}, \{\dot{\phi}_i\}) = \mathcal{L}_{\text{ch}} - \mathcal{L}_J - \mathcal{L}_S$. The charging part reads $\mathcal{L} = \frac{1}{2} \left(\frac{\Phi_0}{2\pi} \right)^2 \dot{\vec{\phi}}^T \mathbf{C} \dot{\vec{\phi}}$ where $\mathbf{C}$ is the capacitance matrix and the phase velocities have been arranged in a column vector. The Josephson part reads $\mathcal{L}_J = -\sum_j E_{J,i} \cos \phi_i = U_J(\phi_1, \phi_2, \phi_3)$ where the Josephson energies are given through the critical currents by $E_{J,i} = \Phi_0 I_{c,i} / 2\pi$. The work done by the voltage sources, finally, is counted as $\mathcal{L}_S = -\frac{\Phi_0}{2\pi} \vec{V}^T \mathbf{C}_g \dot{\vec{\phi}}$. In our case the capacitance matrix is, using the notation from Fig. (1)

$$\mathbf{C} = \begin{pmatrix} C_8 + C_1 + C_3 & -C_1 & C_8 \\ -C_1 & C_1 + C_2 + C_7 & C_7 \\ C_8 & C_7 & C_7 + C_8 + C_\Sigma \end{pmatrix}, \quad (1)$$

where $C_\Sigma = C_4 + C_5 + C_6$ is the total capacitance of the transistor, and the source term is given by

$$\vec{Q}_g = C_g \vec{V} = \begin{pmatrix} 0 \\ 0 \\ -C_5 V_x - C_6 V_T \end{pmatrix} \quad (2)$$

From here, we can find the canonical variables and the Hamiltonian

$$\mathcal{H} = \frac{1}{2} \left(\frac{2\pi}{\Phi_0} \right)^2 \left(\vec{P} - \frac{\Phi_0}{2\pi} \vec{Q}_g \right)^T \mathbf{C}^{-1} \left(\vec{P} - \frac{\Phi_0}{2\pi} \vec{Q}_g \right) - U_J(\phi_1, \phi_2, \phi_3). \quad (3)$$

The canonical momentum $\vec{P}$ is given by $\vec{P} = \left(\frac{\Phi_0}{2\pi} \right)^2 \mathbf{C} \dot{\vec{\phi}} + \frac{\Phi_0}{2\pi} \vec{Q}_g$. We want to rewrite this Hamiltonian now as $H = H_q + H_{\text{q,SET}} + H_{\text{SET}}$. From Eq. (3) we see that the coupling between the transistor and the qubit has the form of $-i\partial_{\phi_k} P_3$. This coupling term can, as well as the coupling to voltage sources, be transformed into phase factors by a gauge transformation $\psi(\vec{\phi}) \rightarrow \psi(\vec{\phi}) \exp \left(-i \int \hat{P}_3 d\vec{\phi} \right)$. This results in a qubit Hamiltonian in phase representation of the same shape as Ref. 13, with a slightly modified capacitance matrix. Performing the two level approximation leads to $H'_q = \frac{1}{2} \begin{pmatrix} \epsilon & \Delta \\ \Delta^* & -\epsilon \end{pmatrix}$

with $\Delta = |\Delta| e^{i\chi}$ where $\hat{\chi} = \delta\phi \hat{P}_3$ and $\delta\phi$, the separation of the minima in the potential landscape corresponding to the persistent current states⁶. In this gauge the charging part of the transistor island has its standard form $E_C(n_L - n_R - n_g)^2 + 2eV(\kappa n_L + (1 - \kappa)n_R)$, where $n_{L/R}$ is the number of charges that have tunneled through the left/right junction and $n_L - n_R$ is the number of extra charges on the transistor island, $\kappa = C_R / (C_L + C_R)$ will be assumed to be 1/2 through the rest of this paper. $C_L = C_6$ and $C_R = C_4 + C_5 + C_6 + C_7 + C_8$ are the effective left/right capacitances of the transistor and n_x is the dimensionless gate voltage. As $E_{c,\text{SET}} \gg E_{J,\text{SET}}$, we can perform a two level approximation also for the transistor island. In order to simplify the treatment of the external Josephson junctions, we observe that the phase χ measures the charge tunneling through the SETs and obtain the qubit-transistor interaction:

$$(H_q + H_{\text{q,SET}})' = \frac{1}{2} \begin{pmatrix} \epsilon & \Delta e^{i\phi N} \\ \Delta e^{-i\phi N} & -\epsilon \end{pmatrix}. \quad (4)$$

Here ϕ is a constant set by the geometric capacitances of the circuit. At the flux degeneracy point, we have $\epsilon = 0$. By performing the unitary transformation $\hat{U} = \exp \left(\frac{i\phi}{2} \hat{\sigma}_z \otimes \hat{\tau}_z \right)$, where σ_z is a Pauli matrix operating in the qubit subspace and τ_z is a Pauli matrix operating in the transistor subspace, we finally obtain

$$\begin{aligned} \hat{H} = & \frac{\Delta}{2} \hat{\sigma}_z + \frac{\delta E_{\text{ch}}}{2} \hat{\tau}_z + E_{J,SET} \hat{1} \otimes \cos \phi \left[\hat{\tau}_+ (\hat{l} + \hat{r}) + \hat{\tau}_- (\hat{l}^\dagger + \hat{r}^\dagger) \right] + i E_{J,SET} \hat{\sigma}_x \otimes \sin \phi \left[\hat{\tau}_+ (\hat{l} + \hat{r}) - \hat{\tau}_- (\hat{l}^\dagger + \hat{r}^\dagger) \right] \\ & + \frac{1}{2} \left(V_T/2 + \sum_i \lambda_i (\alpha_i + \alpha_i^\dagger) \right) \hat{n}_l + \frac{1}{2} \left(-V_T/2 + \sum_i \mu_i (\beta_i + \beta_i^\dagger) \right) \hat{n}_r + \sum_i \omega_i \alpha_i^\dagger \alpha_i + \sum_i \omega_i \beta_i^\dagger \beta_i. \end{aligned} \quad (5)$$

Here, we already have assumed to operate at the flux degeneracy point $\epsilon = 0$ and we have changed to the energy basis such that $\hat{\sigma}_z$ now describes energy and $\hat{\sigma}_x$ flux eigenstates. $n_{L/R}$ count charges having tunneled to the left and right lead respectively and l/r transfer charges from the left/right lead to the island. Moreover, $\hat{\tau}_\pm$ are the raising and lowering operators for the island charge. As we envision the readout to happen completely on the supercurrent branch (see below), we omit quasiparticle terms. For finding dissipative action and finally observing a voltage signal, one has to include resistors described by the α and β operators, which are modeled as baths of harmonic oscillators along the lines of the familiar $P(E)$ analysis of the Caldeira-Leggett model¹⁴.

This is the starting point for our rate equation study of the readout process. The gauge transformation has turned Aharonov-Casher into Aharonov-Bohm phases. If the qubit is in one of the flux, $\hat{\sigma}_x$, eigenstates, the environment will not induce any transitions of the qubit and the qubit state will only influence the phases of the two tunneling events. Such phase differences cannot be detected in the present geometry, as this would require a closed superconducting loop. Notably, qubit and island charge formally appear to be uncoupled, but are jointly affected by coupling to the superconducting leads. This is a result of our gauge transformation: In the previous gauge, the qubit eigenstates had different phases depending on the eigenstate of $\hat{\tau}_z$, thus if the island charge described by $\hat{\tau}_z$ flips the qubit can also make a transition. Note, that the qubit energy splitting has the same value in both $\hat{\tau}$ states.

When $E_{J,SET} < E_{c,SET}$ and the dimensionless conductance of the junction in the transistor is small, we can treat the tunneling term in the Hamiltonian in Eq. (5) perturbatively. The first two terms of Eq. (5) plus the free leads in the last two terms constitute the unperturbed part. The device has to be biased at $\Delta = \delta E_c$. The eigenlevels of the unperturbed system are shown in Fig. (2). In the ideal case, the parameter ϕ in Eq. (5) is exactly $\pi/2$. In this case tunneling through the junctions of the transistor is only possible if, at the same time, the qubit also switches. As a charge tunnels through first the left, then the right junction (corresponding to following the right-going arrow in Fig. (2), then the left-going) a charge has been transferred through the transistor, while the qubit and the transistor returns to the original state. This lead to a quantum flip-flop process where the flips of the transistor island as current passes are accompanied by opposite transitions — flops — of the qubit: Charg-




FIG. 2: The eigenlevels of the unperturbed Hamiltonian. The arrows indicate the wanted transitions. The up/down arrows indicate the qubit states and the numbers 1/0 indicate the transistor states.

ing the island relaxes the qubit, discharging the island excites the qubit. All other transitions are suppressed due to symmetry. Thus we get a current running through the transistor if the qubit is in the excited state, but no current in the ground state. By reading out the current running through the transistor the state of the qubit can be detected. As there is no mixing, we can take as much time to read out the state as we want. Remarkably, if after the measurement the transistor island is uncharged, the post-measurement state is the qubit eigenstate corresponding to the measured observable without relaxation. This is the same outcome as in a QND measurement, even though the Hamiltonian does *not* satisfy the QND condition⁷ and the qubit *does* make transitions during the operation. This result is owed to the flip-flop symmetry of the Hamiltonian. The tunneling probability per second is constant leading to a Poissonian current distribution, which means that arbitrary large resolution is available in this ideal limit by reading out during arbitrarily long time.

An important note is that if the qubit is initially in a superposition of its eigenstates (remember, that eigenstates at the degeneracy point are themselves equal superpositions of current states), a single charge cycle in the transistor will destroy the coherence of the qubit. As a single charge cycle can in principle be detected with the method of Ref. 15, this is a quantum-limited measurement.

For the non-ideal case, the parameter ϕ in eq. (5) is not exactly $\pi/2$ and we have unwanted transitions that lead to mixing of the qubit. As ϕ depends on the capacitor setup, adjusting it with high precision appears to be dif-

ficult. In that case, there is a risk of making a transition to the $|\downarrow 0\rangle$ state by spontaneous emission to the environment, see Fig. 2, which halts the detection process and potentially falsifies the result. Thus, we need to find a detection scheme which suppresses spontaneous emission, i.e. which has an effective spectral density peaked around zero.

This can be done by using incoherent Cooper pair tunneling^{16,17}. By putting an impedance in series with the transistors the supercurrent of the transistor is suppressed. The fluctuations of the voltage across the junction leads instead to an incoherent transfer of Cooper pairs. Still, the energy of the Cooper pair condensate defines a preferred tunneling window and leads to the desired band-pass property. The strong coupling this setup provides and the large qubit splitting compared to the temperature of the oscillator bath makes the bandpass properties quite accentuated which combined with the symmetry properties should result in a good signal to noise ratio.

The incoherent rates can be calculated using standard $P(E)$ theory for an Ohmic environment¹⁴, using

$$P(E) = \begin{cases} 0 & E < -k_B T/g \\ 1/T & |E| < k_B T/g \\ 2/gE & E \gg k_B T/g \end{cases} \quad (6)$$

where g is the dimensionless conductance of the environment. An example of $P(E)$ is shown in Fig. 3. Thus,




FIG. 3: $P(E)$ for an ohmic environment for different resistance of the environment. The junction capacitance used was 0.25 fF and the temperature was 25 mK. Note the lin-log scale.

the rates for the wanted processes are $\Gamma \simeq \sin^2(\phi)/T$ whereas the unwanted one is $\Gamma_{\text{error}} \simeq \cos^2(\phi)2/gE$ where $E \simeq 2E_c$ is the energy gain of a transition to the dark $|0 \downarrow\rangle$ state. This way, we can transfer a number of $N = \Gamma/\Gamma_{\text{error}} = (gE/2T) \tan^2(\phi)$ Cooper pairs through the device before an error occurs, setting an error window for the measurement time of $t_{\text{error}} \simeq N/I$ where I is the average current.

Using the results from Fig. 3 with a resistance of 50 Ω , this ratio can be estimated to several thousand Cooper pairs. Considering present day technology where single Cooper pairs can be counted¹⁵, this can be straightforwardly detected.

This setup has several advantages compared to other setups. For instance it allows for a flux qubit read out on the flux degeneracy point as well a read out for arbitrary small qubit inductance. Because it uses geometric phases to couple the qubit and the pointer it does not require the qubit to move into a mixed charge-flux regime¹⁸. This should make the qubit insensitive to charge noise while at the same time maintaining insensitivity to flux noise to first order. The physics behind the coupling is also quite general meaning that it should be possible to adapt this read out scheme to any system containing conjugate variables.

In this letter, we have demonstrated a novel and promising read out scheme for flux qubits using the conjugate variable. It allows for read out on the flux degeneracy point, leading to improved noise insensitivity. Using incoherent Cooper pair tunneling as a form of bandpass filtering the two different qubit states can be distinguished and detected. The strong coupling provided by the setup allows the bandpass filter to, in the low temperature regime, provide a good signal to noise ratio. We have identified an ideal working point in which the measurement has QND-like properties and is quantum-limited.

This work was sponsored by the EU through the MANAS Marie Cure training site and the IST-SQUBIT2 project. FKW acknowledges support of the DFG through SFB 631 and ARDA and ARO under contract number P-43385-PH-QC.

* Electronic address: wilhelm@theorie.physik.uni-muenchen.de

¹ Y. Makhlin, G. Schön, and A. Shnirman, Rev. Mod. Phys. **73**, 357 (2001).

² C. van der Wal *et al.*, Science **290**, 77 (2000).

³ I. Chiorescu, Y. Nakamura, C. Harmans, and J. Mooij, Science **299**, 1869 (2003).

⁴ Y. Nakamura, Y. Pashkin, and J. Tsai, Nature **398**, 786 (1999).

⁵ T. Yamamoto *et al.*, Nature **425**, 941 (2003).

⁶ J. Mooij *et al.*, Science **285**, 1036 (1999).

⁷ V. Braginsky and F. Khalili, *Quantum Measurement* (Cambridge University Press, Cambridge, 1995).

⁸ F. K. Wilhelm, Phys. Rev. B **68**, 060503(R) (2003).

⁹ D. Vion *et al.*, Science **296**, 286 (2002).

¹⁰ J. Majer, J. Butcher, and J. Mooij, Appl. Phys. Lett. **80**, 3638 (2002).

¹¹ W. Elion, J. Wachtters, L. Sohn, and J. Mooij, Phys. Rev. Lett. **71**, 2311 (1993).

- ¹² J. Friedman and D. Averin, Phys. Rev. Lett. **88**, 050403 (2002).
- ¹³ T. P. Orlando *et al.*, Phys. Rev. B **60**, 15398 (1999).
- ¹⁴ F. K. Wilhelm, G. Schön, and G. T. Zimányi, Phys. Rev. Lett. **87**, 136802 (2001).
- ¹⁵ O. Astafiev *et al.*, Phys. Rev. B **69**, 180507 (2004).
- ¹⁶ A. J. Rimberg, T. R. Ho, C. Kurdak, and J. Clarke, Phys. Rev. Lett. **78**, 2632 (1997).
- ¹⁷ G.-L. Ingold and Y. V. Nazarov, in *Single Charge Tunneling*, edited by H. Grabert and M. Devoret (Plenum, New York, 1992).
- ¹⁸ M. Amin, Phys. Rev. B **71**, 024504 (2005).